



**Portable Hand-operated 3-phase starter for D-O-L start of pumps with thermal contacts built-in.**

**Type:** START 351  
**Voltage:** 3 x 380 - 415V, 3 x 500V, 3 x 230V  
**Frequency:** 50-60 Hz  
**Current range:** 1,0 – 32 A  
**Overload protection:** Thermal/magnetic overload protection  
**Monitoring:** Monitoring of thermal contacts with manual reset  
Phase sequence indicator.  
**Connection supply:** Terminal connection with cable glands  
**Connection pump:** Terminal connection with cable glands  
**General:** Degree of protection IP55  
Size 285 x 110 x 95 mm  
Weight 0,8 kg  
CE-marked

Type	Voltage (V)	Current range (A)	Supply cable Ø (mm)	Pump cable Ø (mm)	Part no.	
START 351-400-B-PG-	3 x 380 3 x 400 3 x 415	1,6	1,0 - 1,6	11 - 17	11 - 21	554 30 40
		2,5	1,6 - 2,5	-"	-"	554 30 41
		4	2,5 - 4,0	-"	-"	554 30 42
		6	4 - 6,3	-"	-"	554 30 43
		10	6 - 10	-"	-"	554 30 44
		14	9 - 14	-"	-"	554 30 45
		18	13 - 18	-"	-"	554 30 46
		23	17 - 23	-"	-"	554 30 47
		25	20 - 25	-"	-"	554 30 48
		32	24 - 32	-"	18 - 25	554 30 49
START 351-500-B-PG-	3 x 500	1,6	1,0 - 1,6	11 - 17	11 - 21	554 30 50
		2,5	1,6 - 2,5	-"	-"	554 30 51
		4	2,5 - 4,0	-"	-"	554 30 52
		6	4 - 6,3	-"	-"	554 30 53
		10	6 - 10	-"	-"	554 30 54
		14	9 - 14	-"	-"	554 30 55
		18	13 - 18	-"	-"	554 30 56
		23	17 - 23	-"	-"	554 30 57
		25	20 - 25	-"	-"	554 30 58
		32	24 - 32	-"	18 - 25	554 30 59
START 351-230-B-PG-	3 x 230	1,6	1,0 - 1,6	11 - 17	11 - 21	554 30 60
		2,5	1,6 - 2,5	-"	-"	554 30 61
		4	2,5 - 4,0	-"	-"	554 30 62
		6	4 - 6,3	-"	-"	554 30 63
		10	6 - 10	-"	-"	554 30 64
		14	9 - 14	-"	-"	554 30 65
		18	13 - 18	-"	-"	554 30 66
		23	17 - 23	-"	-"	554 30 67
		25	20 - 25	-"	-"	554 30 68
		32	24 - 32	-"	18 - 25	554 30 69